

BS 18 LT BL Q (602334890) Cordless drill / screwdriver

Order No. 602334890
EAN 4007430302335



Representative picture



- A powerful all-around choice: easy to handle drill with brushless power for challenging drilling and screw fitting applications
- Metabo quick system: quick exchange of chucks, bit holders, angle adapters and more for flexible work
- Spindle with magnetic hexagon recess for screwdriver bits for working without chuck
- Powerful Brushless motor for greatest efficiency and long battery pack runtime
- Overload protection: protects the motor from overheating
- Integrated LED work light with afterglow function for optimal brightness in the work area
- With handy belt hook and bit case which can be fixed either on the right or left side
- Many brands, one battery pack system: This product can be combined with all 18V battery packs and chargers of the CAS brands: www.cordless-alliance-systems.com

Technical values

KEY FIGURES

Battery voltage	18 V
Maximum torque, soft	34 Nm / 301 in-lbs
Maximum torque, hard	75 Nm / 663.8 in-lbs
Adjustable torque	0.7 - 8 Nm // 6 - 71 in-lbs
Drill Ø steel	13 mm / 1/2 "
Drill-Ø soft wood	38 mm / 1 1/2 "

No-load speeds	0 - 600 / 0 - 2100 rpm
----------------	------------------------

Chuck capacity	1.5 - 13 mm // 1/16 - 1/2 "
----------------	-----------------------------

Weight without battery pack	1.3 kg / 2.9 lbs
-----------------------------	------------------

Weight with battery pack	1.7 kg / 3.7 lbs
--------------------------	------------------

VIBRATION

Drilling in metal	2.3 m/s ²
-------------------	----------------------

Uncertainty of measurement K	1.5 m/s ²
------------------------------	----------------------

NOISE EMISSION

Sound pressure level	77 dB(A)
----------------------	----------

Sound power level (LwA)	88 dB(A)
-------------------------	----------

Uncertainty of measurement K	3 dB(A)
------------------------------	---------

Scope of delivery

- Quick-change chuck
- Quick-change bit holder
- Belt hook and bit case
- without battery pack, without charger