

KH 18 LTX BL 24 Q (601714850) Cordless combination hammer

Order No. 601714850

EAN 4061792218543



Representative picture



- Extremely light and compact cordless hammer with integrated extraction interface
- Maximum drill performance, efficiency and service life thanks to brushless technology and high-performance hammer action
- Dust-free drilling with compact dust extraction ISA 24 (accessory)
- Combination hammer with 3 functions: hammer drilling, drilling and chiselling
- Metabo VibraTech (MVT): integrated damping system to reduce vibrations in order to protect the user's health
- Metabo Quick: quick change between SDS Plus hammer chuck and keyless chuck for many different applications
- Vario-Tacho-Constamatic (VTC)-Full Wave Electronics for work with materials requiring customised speeds, which remain constant under load
- Electronic soft start for precise spot-drilling
- Double safety when the drill bit jams: No kick-back thanks to the mechanic decoupling plus ultra-fast sensor-controlled shutdown
- LED work light for optimum view of the drilling site
- Many brands, one battery pack system: This product can be combined with all 18V battery packs and chargers of the CAS brands: www.cordless-alliance-systems.com

Technical values

KEY FIGURES

Battery voltage

18 V

Max. single blow energy (EPTA)	2.2 J
Maximum impact rate	4750 bpm
Drill-Ø concrete with hammer drills	24 mm / 1 "
Drill-Ø masonry with core bits	82 mm / 3 7/32 "
Drill Ø steel	13 mm / 1/2 "
Drill-Ø soft wood	30 mm / 1 3/16 "
No-load speed	0 - 1280 rpm
Tool holder	SDS-plus
Weight without battery pack	3 kg / 6.61 lbs

VIBRATION

Hammer drilling concrete	13.4 m/s ²
Uncertainty of measurement K	1.5 m/s ²
Chiseling	9.1 m/s ²
Uncertainty of measurement K	1.5 m/s ²

NOISE EMISSION

Sound pressure level	90 dB(A)
Sound power level (LwA)	101 dB(A)
Uncertainty of measurement K	3 dB(A)

Scope of delivery

- Hammer chuck for tools with SDS-plus shank end
- Keyless chuck for tools with cylindrical shank
- rubber-coated side handle
- Drilling depth guide
- without battery pack, without charger